

A Comprehensive Review of Reliability Prediction and Enhancement in Transparent Thin-Film Transistors

A. Mani kandan^{*1}, Dr. T. Sivakumar²

^{*1}Assistant Professor, Department of Electronics and Communication, Sri Ganesh College of Arts & Science (Autonomous), Salem, Tamilnadu, India.

²Professor, Department of Electronics, RVS College of Arts & Science (Autonomous), Coimbatore, Tamilnadu, India.

*Corresponding author

How to cite this paper:

A. Mani kandan^{*1}, Dr. T. Sivakumar², "A Comprehensive Review of Reliability Prediction and Enhancement in Transparent Thin-Film Transistors", IJIRE-V7I4-233-241.



Copyright © 2026
by author(s) and
Fifth Dimension
Research

Publication. This work is licensed under the
Creative Commons Attribution International
License (CC BY 4.0).

<http://creativecommons.org/licenses/by/4.0/>

Abstract: Transparent Thin Film Transistors (TTFTs) have emerged as a promising technology for next-generation flexible electronics, transparent displays, wearable devices, biomedical sensors, and Internet of Things (IoT) applications due to their transparency, low power consumption, and compatibility with large-area fabrication processes. Despite their significant advantages, the long-term reliability and operational stability of TTFTs remain major challenges that limit their widespread commercial deployment. Device degradation caused by bias stress, thermal effects, environmental factors, and material defects can lead to threshold voltage shifts, mobility degradation, reduced ON/OFF current ratios, and shortened device lifetime. In recent years, Machine Learning (ML) and Deep Learning (DL) techniques have been increasingly adopted to predict device degradation, estimate lifetime, and model reliability characteristics. This review presents a comprehensive analysis of predictive analytics approaches for TTFT reliability enhancement using advanced machine learning and deep learning techniques. The study examines conventional machine learning models, deep neural networks, recurrent learning architectures, and hybrid intelligent systems employed for reliability prediction and degradation analysis. Furthermore, the strengths, limitations, and performance of existing approaches are critically evaluated with respect to prediction accuracy, interpretability, adaptability, and computational efficiency. The review identifies key research gaps, including the absence of explainable prediction frameworks, dynamic degradation monitoring models, and optimization-driven reliability improvement strategies. Finally, emerging research directions involving Explainable Artificial Intelligence (XAI), digital twins, physics-informed learning, and optimization algorithms such as Genetic Algorithms and Particle Swarm Optimization are discussed to support the development of next-generation reliability enhancement frameworks for Transparent Thin Film Transistors.

Key Words: Transparent Thin Film Transistor (TTFT); Reliability enhancement; Degradation prediction; Particle Swarm Optimization.

I. INTRODUCTION

The rapid advancement of modern electronic technologies has created a growing demand for flexible, lightweight, transparent, and energy-efficient electronic devices. Transparent Thin Film Transistors (TTFTs) have emerged as one of the most promising semiconductor technologies for next-generation electronic systems due to their unique combination of optical transparency, mechanical flexibility, low manufacturing cost, and compatibility with large-area fabrication processes. These characteristics make TTFTs highly suitable for a wide range of applications, including transparent displays, flexible displays, wearable electronics, biomedical monitoring systems, smart windows, Internet of Things (IoT) devices, environmental sensors, and advanced human-machine interfaces. As industries continue to move toward flexible and transparent electronics, ensuring the long-term reliability and operational stability of TTFTs has become a critical research challenge^{[1][2]}. A Transparent Thin Film Transistor is a field-effect transistor fabricated using transparent semiconductor materials such as zinc oxide (ZnO), indium gallium zinc oxide (IGZO), tin oxide (SnO₂), and related metal oxide compounds. These materials provide excellent optical transparency while maintaining desirable electrical properties. Compared with conventional silicon-based transistors, TTFTs offer several advantages, including lower fabrication temperatures, reduced production costs, and improved compatibility with flexible substrates. However, despite these benefits, TTFTs are susceptible to various degradation mechanisms that significantly affect their electrical performance and operational lifetime^{[3][4][5]}.

Reliability is one of the most important performance indicators for semiconductor devices. In TTFTs, reliability refers to the ability of a device to maintain its electrical characteristics and functional performance over an extended period under varying operating conditions. Several factors contribute to device degradation, including positive bias stress, negative bias stress, thermal stress, environmental exposure, humidity, oxygen interaction, charge trapping, interface defects, and material instability^{[6][7]}. These degradation mechanisms often result in threshold voltage shifts, mobility degradation,

increased leakage current, reduced ON/OFF current ratio, and deterioration of switching performance. Such reliability issues limit the commercial adoption of TTFT-based systems in critical applications where long-term stability and predictable performance are essential^[8].

Traditionally, reliability assessment of TTFTs has been performed using experimental stress testing and physics-based degradation models. Accelerated lifetime testing methods are commonly employed to evaluate device behavior under different stress conditions^[9]. While these techniques provide valuable insights into degradation mechanisms, they often require extensive experimentation, significant computational resources, and long observation periods. Furthermore, conventional reliability models may struggle to accurately capture the complex nonlinear interactions between material properties, environmental factors, and operational parameters. As TTFT structures become increasingly sophisticated, there is a growing need for intelligent approaches capable of analyzing large volumes of experimental data and predicting device reliability with greater accuracy and efficiency.

The emergence of Artificial Intelligence (AI), Machine Learning (ML), and Deep Learning (DL) technologies has transformed the field of predictive analytics across various engineering domains. Machine learning techniques have demonstrated remarkable capabilities in identifying hidden patterns, modeling nonlinear relationships, and making accurate predictions from large datasets. In semiconductor reliability research, ML algorithms such as Linear Regression, Support Vector Machines, Decision Trees, Random Forests, and Artificial Neural Networks have been utilized to predict threshold voltage shifts, estimate device lifetime, and analyze degradation characteristics. More recently, deep learning architectures including Deep Neural Networks (DNNs), Convolutional Neural Networks (CNNs), Recurrent Neural Networks (RNNs), and Long Short-Term Memory (LSTM) networks have shown significant promise in capturing complex degradation behaviors and improving prediction accuracy^[10-13].

The primary objective of this review is to critically examine machine learning and deep learning techniques employed for reliability prediction and enhancement in Transparent Thin Film Transistors. The study systematically analyzes existing approaches for degradation prediction, threshold voltage estimation, lifetime assessment, and reliability modeling. Furthermore, the strengths, limitations, and performance characteristics of various predictive models are comparatively evaluated. Special attention is given to research challenges related to black-box prediction, dynamic degradation modeling, optimization-based reliability enhancement, and explainable decision-making. Finally, future research directions are identified to support the development of intelligent, adaptive, and optimization-driven frameworks capable of improving TTFT reliability and extending device lifetime.

The remainder of this paper is organized as follows. Section 2 presents the fundamentals of Transparent Thin Film Transistors and their reliability characteristics. Section 3 discusses machine learning and deep learning techniques applied to reliability prediction. Section 4 reviews existing literature on TTFT reliability analysis. Section 5 provides a comparative assessment of current predictive models. Section 6 identifies major research gaps and limitations. Section 7 explores emerging technologies and future research directions. Finally, Section 8 concludes the paper and summarizes the key findings.

II. FUNDAMENTALS OF TTFT RELIABILITY ANALYSIS

Transparent Thin Film Transistors (TTFTs) are advanced semiconductor devices fabricated using transparent conductive and semiconducting materials, enabling both electrical functionality and optical transparency. Unlike conventional silicon-based transistors, TTFTs can be manufactured on glass, plastic, and flexible substrates, making them suitable for emerging applications such as transparent displays, wearable electronics, smart windows, biomedical sensors, flexible circuits, and Internet of Things (IoT) devices^[14].

A typical TTFT consists of four major components:

- Transparent semiconductor layer
- Gate dielectric layer
- Source and drain electrodes
- Substrate

Common semiconductor materials used in TTFT fabrication include Zinc Oxide (ZnO), Indium Gallium Zinc Oxide (IGZO), Tin Oxide (SnO₂), and other metal oxide semiconductors. These materials offer high optical transparency, low-temperature processing capability, and satisfactory carrier mobility. Despite these advantages, TTFTs often experience performance degradation under prolonged operation, making reliability analysis a critical aspect of device design and commercialization.

Importance of Reliability in TTFTs

Reliability refers to the ability of a TTFT to maintain its intended electrical and functional performance over a specified period under normal operating conditions^[15-16]. High reliability is essential because TTFT-based devices are increasingly deployed in applications where long-term stability and consistent operation are mandatory.

Poor reliability can lead to:

- Reduced device lifetime
- Performance degradation
- Increased power consumption
- Failure of electronic systems
- Increased maintenance costs

Therefore, understanding degradation mechanisms and predicting device behavior under stress conditions are crucial for enhancing TTFT performance and extending operational lifetime.

Key Reliability Parameters

The reliability of TTFTs is generally evaluated using several electrical performance parameters.

Threshold Voltage (V_{th}):

Threshold voltage is the minimum gate voltage required to create a conducting channel between the source and drain terminals. Mathematically,

$$V_{th} = V_G \text{ when } I_{DS} \text{ begins conduction}$$

where:

V_{th} = Threshold voltage; V_G = Gate voltage; I_{DS} = Drain current

A shift in threshold voltage is one of the most common indicators of TTFT degradation.

Carrier Mobility (μ)

Carrier mobility determines how efficiently charge carriers move through the semiconductor channel.

$$\mu = (L/W C_{ox} V_{DS}) \times (\partial I_{DS} / \partial V_{GS})$$

where:

μ = Mobility; L = Channel length; W = Channel width; C_{ox} = Gate oxide capacitance; V_{DS} = Drain-source voltage; V_{GS} = Gate-source

Reduced mobility generally indicates device degradation.

ON/OFF Current Ratio:

The ON/OFF ratio measures switching performance:

$$\text{ON/OFF Ratio} = I_{ON} / I_{OFF}$$

where:

I_{ON} = Current in ON state; I_{OFF} = Current in OFF state

Higher values indicate better switching behaviour and device reliability.

Subthreshold Swing (SS):

Subthreshold swing measures how efficiently the transistor switches from OFF to ON state.

$$SS = dV_{GS} / d(\log I_{DS})$$

Lower values indicate better switching efficiency and reduced power consumption.

Degradation Mechanisms in TTFTs

Several physical phenomena contribute to TTFT degradation.

Positive Bias Stress (PBS)

Positive gate voltage applied for prolonged periods causes charge trapping within the dielectric layer.

Effects:

- Threshold voltage shift
- Mobility reduction
- Increased leakage current

Negative Bias Stress (NBS):

Negative gate voltage stress affects charge transport characteristics and interface stability. Effects:

- Instability in device operation
- Threshold voltage variation

Thermal Stress:

High operating temperatures accelerate material degradation and defect generation. Effects:

- Carrier mobility degradation
- Increased defect density
- Shortened device lifetime

Environmental Stress:

Environmental factors such as humidity, oxygen exposure, and ultraviolet radiation significantly influence TTFT performance.

Effects:

- Surface contamination
- Oxidation
- Electrical instability

Reliability Testing Methods

Reliability testing evaluates device performance under accelerated stress conditions^[17].

Accelerated Lifetime Testing (ALT):

Devices are subjected to elevated temperatures and voltages to accelerate degradation. Benefits:

- Faster reliability assessment
- Lifetime estimation

Bias Temperature Stress (BTS) Combines electrical and thermal stress. Input Parameters:

- Temperature
- Gate Voltage
- Stress Time Output Parameters:
- Threshold Voltage Shift
- Mobility Variation

Environmental Stress Testing

Evaluates device behavior under varying humidity and atmospheric conditions.

Mathematical Models for Reliability Analysis

Threshold Voltage Shift Model:

One commonly used model is:

$$\Delta V_{th} = A \times t^n$$

This equation describes the increase in degradation with operating time.

Stretched Exponential Model:

A widely adopted degradation model is:

$$\Delta V_{th}(t) = \Delta V_0 [1 - \exp\{-(t/\tau)^\beta\}]$$

This model accurately represents long-term degradation behaviour.

Arrhenius Lifetime Model:

The Arrhenius equation predicts temperature-dependent lifetime.

$$\text{Lifetime} = A \exp(E_a/kT)$$

Higher temperatures generally reduce device lifetime.

Machine Learning Perspective of Reliability Analysis

Traditional reliability analysis relies heavily on physical models and experimental measurements^[18-20]. However, modern TTFT devices generate large volumes of data during stress testing and operation.

Machine learning techniques enable:

- Threshold voltage prediction
- Lifetime estimation
- Degradation forecasting
- Failure classification
- Reliability optimization

Typical input features include:

$$X = \{\text{Stress Time, Temperature, Gate Voltage, Material Properties}\}$$

Typical outputs include:

$$Y = \{\text{Threshold Voltage Shift, Degradation Rate, Device Lifetime}\}$$

Deep learning models can identify nonlinear relationships between input parameters and reliability characteristics, enabling more accurate prediction than conventional analytical methods.

Challenges in TTFT Reliability Analysis

Although significant progress has been achieved, several challenges remain:

- Complex degradation mechanisms
- Nonlinear device behavior
- Limited experimental datasets
- Black-box prediction models
- Lack of explainability
- Absence of real-time monitoring systems
- Limited optimization strategies

Addressing these challenges requires intelligent reliability frameworks capable of combining predictive analytics, explainable artificial intelligence, and optimization techniques.

Reliability Parameters

- Threshold Voltage Shift
- Mobility Degradation
- ON/OFF Current Ratio
- Subthreshold Swing

Failure Mechanisms

- Bias Stress Effects
- Thermal Stress
- Environmental Degradation
- Material Defects

Model	Stress Factors Considered	Complexity	Accuracy
Arrhenius	Temperature	Low	Medium
Power Law	Time	Low	Medium
Stretched Exponential	Charge Trapping	Medium	High
Eyring	Temperature + Voltage	Medium	High
Weibull	Failure Statistics	Medium	High
Machine Learning	Multiple Factors	High	Very High
Deep Learning	Dynamic Multi-factor Data	Very High	Excellent

Table 1: Comparative Analysis of Lifetime Models

Research Perspective

Most existing TTFT studies focus on predicting device lifetime rather than improving it. Furthermore, conventional models provide limited insights into degradation causes and often assume static operating conditions. Future research should integrate deep learning, explainable artificial intelligence, and optimization algorithms such as Genetic Algorithms (GA) and Particle Swarm Optimization (PSO) to develop intelligent reliability enhancement frameworks capable of predicting, explaining, and minimizing device degradation while maximizing operational lifetime.

III. REVIEW OF EXISTING RESEARCH ON TTFT RELIABILITY PREDICTION

S.No	Author(s) & Year	Technique/Model Used	Input Parameters	Output Parameters	Major Contribution	Limitations
1	Nomura et al. (2022)	Artificial Neural Network (ANN)	Gate Voltage, Temperature, Stress Time	Threshold Voltage Shift	Predicted device degradation with improved accuracy over conventional methods	Black-box prediction; no failure explanation
2	Kim et al. (2022)	Random Forest Regression	Electrical Stress Parameters	Device Lifetime	Reliable lifetime estimation under bias stress conditions	Limited adaptability to dynamic environments
3	Wang et al. (2022)	Support Vector Machine (SVM)	Mobility, Threshold Voltage, Stress Time	Reliability Classification	Improved classification of device health states	Limited performance for large datasets

4	Zhang et al. (2023)	Deep Neural Network (DNN)	Voltage, Temperature, Material Properties	Threshold Voltage Prediction	Enhanced prediction accuracy using deep learning	No optimization framework
5	Lee et al. (2023)	Convolutional Neural Network (CNN)	Experimental Reliability Data	Degradation Pattern Recognition	Automated feature extraction from reliability data	High computational requirements
6	Chen et al. (2023)	Long Short-Term Memory (LSTM)	Time-Series Stress Data	Future Degradation Curve	Effective modeling of temporal degradation behavior	Lack of explainability
7	Park et al. (2023)	Hybrid ANN-SVM Model	Stress Conditions, Device Characteristics	Remaining Useful Life (RUL)	Improved prediction stability	Static prediction framework
8	Kumar et al. (2024)	Deep Learning Framework	Bias Stress Parameters	Lifetime Estimation	Accurate long-term reliability prediction	No reliability enhancement strategy
9	Liu et al. (2024)	Recurrent Neural Network (RNN)	Continuous Monitoring Data	Dynamic Reliability Assessment	Captured time-dependent degradation trends	Limited optimization capabilities
10	Ahmed et al. (2024)	Ensemble Learning Model	Electrical and Thermal Parameters	Failure Prediction	Improved prediction robustness	Inability to identify root causes of failure
11	Singh et al. (2025)	Explainable AI (XAI) Framework	Device Stress Parameters	Reliability Interpretation	Improved transparency of prediction models	Limited application to TFTs
12	Zhao et al. (2025)	Physics-Informed Neural Network (PINN)	Material and Physical Parameters	Degradation Prediction	Combined physics knowledge with AI predictions	Complex model development
13	Patel et al. (2025)	Deep Learning + Optimization	Voltage, Temperature	Lifetime Enhancement Recommendations	Introduced optimization-based reliability improvement	Limited real-time implementation
14	Huang et al. (2026)	Digital Twin-Based Monitoring	Real-Time Sensor Data	Reliability Monitoring	Continuous device health assessment	High implementation cost
15	Proposed Research Direction	Dynamic Deep Learning + XAI + GA/PSO	Stress Time, Temperature, Voltage, Material Properties	Degradation Prediction, Failure Cause Analysis, Lifetime Enhancement	Predicts, explains, and optimizes device reliability simultaneously	Research yet to be explored

Table 2. Summary of Existing Research on TTFT Reliability Prediction and Enhancement

Observations

- Most existing studies focus primarily on threshold voltage prediction and lifetime estimation.
- Artificial Neural Networks and Deep Learning models provide higher prediction accuracy compared to traditional statistical methods.
- LSTM and RNN models are increasingly used for modeling time-dependent degradation processes.
- Existing approaches mainly provide predictions but do not offer mechanisms to improve device reliability.
- Most deep learning frameworks operate as black-box models and lack interpretability.

- Explainable Artificial Intelligence (XAI) applications in TTFT reliability prediction remain limited.
- Dynamic degradation monitoring and real-time reliability assessment are still underexplored.
- Optimization algorithms such as Genetic Algorithms (GA) and Particle Swarm Optimization (PSO) are rarely integrated with reliability prediction frameworks.
- Current research focuses on identifying failures rather than explaining why failures occur and how they can be prevented.

Research Gap Identified

The literature reveals that existing TTFT reliability studies predominantly concentrate on degradation prediction and lifetime estimation. However, there is a lack of integrated frameworks that combine deep learning, explainable artificial intelligence, dynamic degradation modeling, and optimization techniques to proactively enhance device reliability. Therefore, future research should focus on developing intelligent reliability enhancement systems capable of predicting degradation, identifying root causes of failure, recommending optimal operating conditions, and extending device lifetime through adaptive optimization strategies.

Comparison Parameters:

- Prediction Accuracy
- Computational Complexity
- Interpretability
- Reliability Improvement capability
- Lifetime Prediction Accuracy

Model	Strength	Weakness	TTFT Suitability
ANN	Simple	Overfitting	Medium
SVM	Good with small datasets	Poor scalability	Medium
Random Forest	Robust	Limited temporal modeling	Medium
CNN	Feature extraction	Needs large datasets	High
LSTM	Time-series degradation	Training cost	Very High
Transformer	Long-range dependencies	High computational cost	Excellent

Table 3: Comparative Performance Analysis

IV.PROPOSED RESEARCH FRAMEWORK




Figure 1: Conceptual Architecture

Expected Contributions

- Dynamic degradation prediction
- Failure root-cause identification
- Explainable prediction
- Reliability enhancement
- Lifetime optimization

V.CONCLUSION

Transparent Thin Film Transistors (TTFTs) have emerged as a key enabling technology for next-generation transparent and flexible electronic systems, finding applications in wearable devices, transparent displays, biomedical sensors, smart windows, and Internet of Things (IoT) platforms. However, reliability degradation caused by electrical stress, thermal effects, material defects, and environmental conditions continues to hinder their large-scale commercial adoption. Accurate prediction and enhancement of device reliability are therefore essential to ensure long-term operational stability and improved performance. This review comprehensively examined the existing research on TTFT reliability prediction using machine learning and deep learning techniques. Various predictive approaches, including Artificial Neural Networks (ANNs), Support Vector Machines (SVMs), Deep Neural Networks (DNNs), Recurrent Neural Networks (RNNs), and Long Short-Term Memory (LSTM) models, were analysed with respect to their prediction capabilities, adaptability, and effectiveness in modelling degradation behaviour. The comparative assessment revealed that deep learning-based approaches offer superior accuracy in predicting threshold voltage shifts, degradation trends, and device lifetime compared to traditional analytical methods. Nevertheless, current studies largely focus on prediction rather than proactive reliability enhancement and often suffer from limitations such as black-box decision-making, limited interpretability, static degradation modelling, and lack of optimization mechanisms.

The review further identified significant research gaps and highlighted emerging opportunities involving Explainable Artificial Intelligence (XAI), Digital Twin technology, Physics-Informed Neural Networks, and evolutionary optimization techniques such as Genetic Algorithms and Particle Swarm Optimization. Integrating these technologies with deep learning frameworks can facilitate dynamic degradation monitoring, root-cause analysis, reliability optimization, and lifetime extension. Future research should focus on developing intelligent, explainable, and adaptive reliability enhancement frameworks capable of simultaneously predicting, interpreting, and mitigating degradation in TTFTs, thereby supporting the advancement of robust and sustainable transparent electronic systems.

References

- [1] S. Jeong, J. Kim, and H. J. Kim, "Recent Advances in Oxide Thin-Film Transistors for Flexible and Transparent Electronics," *Advanced Electronic Materials*, vol. 8, no. 3, pp. 1–21, 2022.
- [2] T. Kamiya and H. Hosono, "Material Characteristics and Reliability Issues of Amorphous Oxide Semiconductor Thin-Film Transistors," *NPG Asia Materials*, vol. 14, no. 1, pp. 1–15, 2022.
- [3] Y. Li, X. Zhang, and J. Wang, "Machine Learning Approaches for Semiconductor Device Reliability Prediction: A Review," *Microelectronics Reliability*, vol. 132, pp. 114–126, 2022.
- [4] J. Robertson and R. M. Wallace, "High-k Materials and Reliability Challenges in Advanced Thin Film Devices," *Materials Science in Semiconductor Processing*, vol. 145, pp. 106–118, 2022.
- [5] H. Park, S. Lee, and K. Cho, "Deep Learning-Based Degradation Prediction in Oxide Thin Film Transistors Under Bias Stress Conditions," *Microelectronics Reliability*, vol. 140, pp. 114845, 2023.
- [6] M. Chen, Y. Liu, and X. Zhao, "LSTM-Based Time-Series Reliability Prediction for Semiconductor Devices," *Engineering Applications of Artificial Intelligence*, vol. 124, pp. 106530, 2023.
- [7] R. Singh and P. Sharma, "Artificial Intelligence Techniques for Reliability Assessment of Electronic Devices: A Comprehensive Review," *Microelectronics Reliability*, vol. 143, pp. 114962, 2023.
- [8] X. Wang, Y. Huang, and Z. Li, "Physics-Informed Neural Networks for Reliability Modeling of Thin-Film Electronic Devices," *Applied Soft Computing*, vol. 142, pp. 110370, 2024.
- [9] S. Kumar, A. Verma, and N. Gupta, "Deep Neural Network Framework for Predicting Electrical Degradation in Flexible Thin Film Transistors," *Journal of Intelligent Manufacturing*, vol. 35, no. 2, pp. 781–796, 2024.
- [10] Y. Zhao, J. Chen, and H. Wu, "Data-Driven Reliability Monitoring of Transparent Electronic Devices Using Machine Learning," *Microelectronics Reliability*, vol. 151, pp. 115258, 2024.
- [11] A. Ahmed, M. Hassan, and R. Ibrahim, "Explainable Artificial Intelligence for Semiconductor Reliability Prediction," *Expert Systems with Applications*, vol. 252, pp. 124102, 2025.
- [12] L. Zhang, P. Li, and H. Zhou, "Digital Twin-Assisted Reliability Prediction for Flexible Electronics Manufacturing," *Robotics and Computer-Integrated Manufacturing*, vol. 89, pp. 102760, 2025.
- [13] V. Patel and K. Shah, "Hybrid Deep Learning and Optimization Framework for Lifetime Prediction of Electronic Devices," *Engineering Applications of Artificial Intelligence*, vol. 136, pp. 108970, 2025.
- [14] B. Liu, Y. Sun, and J. Wang, "Real-Time Reliability Enhancement of Thin-Film Devices Using Explainable Deep Learning," *Microelectronics Reliability*, vol. 162, pp. 115810, 2026.
- [15] H. Chen, X. Wu, and Y. Zhang, "Adaptive Reliability Optimization for Transparent Thin Film Transistors Using Deep Learning and Evolutionary Algorithms," *Applied Soft Computing*, vol. 158, pp. 111642, 2026.
- [16] Shen, Y., Zhang, M., He, S., Bian, L., Liu, J., Chen, Z., Xue, S., Zhou, Y., & Yan, Y. (2024). Reliability issues of amorphous oxide semiconductor-based thin film transistors. *Journal of Materials Chemistry C*, 12, 13707–13726
- [17] Kumar, T. S., Hazarika, A., Hazarika, A., Srinivas, P. S. T. N., Tiwari, P. K., & Kumar, A. (2024). A machine learning approach to

- accelerate reliability prediction in nanowire FETs from self-heating perspective. *Microelectronics Reliability*, 161, 115484
- [18] Yuan, C., de Jong, S. D. M., & van Driel, W. D. (2024). AI-assisted Design for Reliability: Review and Perspectives. In *Proceedings of EuroSimE 2024*. IEEE.
- [19] Choi, S., Jang, Y., Guo, Y., Kim, Y.-S., Song, J.-K., & Yi, J. (2026). Reliability Strategies for a-IGZO Thin-Film Transistors Under Stress Environments. *Transactions on Electrical and Electronic Materials*, 27(2), 243–257.
- [20] Huzaibi, H. U., Han, S.-T., & Zhang, M. (2026). Model representation in amorphous metal oxide thin-film transistors: a critical review. *npj Flexible Electronics*, 10, Article 13.
- [21] Rafiee, M., & Saini, P. (2026). Advanced semiconductor packaging design via artificial intelligence and machine learning: A review. *Microelectronics Reliability*, 181, 116145.
- [22] Rafiee, M., & Saini, P. (2026). Advanced semiconductor packaging design via artificial intelligence and machine learning: A review. *Microelectronics Reliability*.
- [23] Manoharan, S. (2026). Study on Thin-Film Transistor and Circuit Design Using Artificial Intelligence. *Journal of Electronics and Informatics*, 7(4), 298–315.